



JST136Q-800D 4A TRAC

Rev. A.1.0

DESIGN

The JST136Q800D triac is suitable for general purpose AC switching applications in phase control applications, inductive motor starting circuits for phase control applications in light dimmer motor speed control etc. From T2 terminal to external heat sink. Page TO-126 is recommended.

PARAMETERS

ABSTRACT

Parameter	Symbol	Value	Unit
Storage temperature range	$T_{sg}$	-40 150	
Operating temperature range	$T_j$	-40 125	
Repetitive peak off-state voltage ( $T_j=25^\circ C$ )	$V_{BM}$	800	V
Repetitive peak reverse voltage ( $T_j=25^\circ C$ )	$V_{RRM}$	800	V
RMS on-state current ( $T_c=83^\circ C$ )	$I_{T(RMS)}$	4	A
Non-repetitive surge peak on-state current (full cycle, $t_p=20ms$ , $T_j=25^\circ C$ )	$I_{TSM}$	35	A
Non-repetitive surge peak on-state current (full cycle, $t_p=16.6ms$ , $T_j=25^\circ C$ )		38.5	
$I^2t$ value for fusing ( $t_p=10ms$ , $T_j=25^\circ C$ )	$I^2t$	6.1	$A^2s$

Off-state reverse current ( $I_G=2xI_{GT}$ ,  $f=100Hz$ ,  $T_j=125^\circ C$ )

ELECTRICAL CHARACTERISTICS

(Tj=25 unless otherwise specified)

Symbol	Test Condition	Quadrant	Value		Unit
IGT	VD=12V RL=33	- -	MAX.	5	mA
				10	
VGT		ALL	MAX.	1	V
VGD	VD=VBM Tj=125 RL=3.3k	ALL	MIN.	0.2	V
IL	IG=1.2IGT	-	MAX.	15	mA
		-		25	
IH	IT=10mA		MAX.	15	(Refer to Tc 0 Tc 0 Tc 0)
(dV/dt)	VD=54V Gate n Tj=110		MIN.	10	V/s
(dI/dt)c	(dI/dt)e 1.8 A/ns Tj=110		MIN.	2.5	



FG1 : Mi numpower di s p a on v s R N  
on-stear rent

FG2: R N on -stear rent v s e  
tempur e




**PARAM**

Order code	Voltage $V_{DRM} / V_{RM}$ (V)	IGT (mA)		Package	Base qty. ( $\mu$ s)	Delivery mode
		-	-			
ST136Q-800D	800	5	10	TO-126	500	Bulk Pack

**Document Revision History**

#	Reason	Tags
Apr.14, 2023	A 1.0	Launched

**ST13600D**

**J eJi eM**

